

# Link to BM Reflectors

## **Time Slot 2 implements the use of reflectors similar to the D-star network.**

The way to use the reflector is to program your radio with Talk Group 9 in Time Slot 2.  
(Add 9 in contact as GROUP. Make a Channel up for TG9. Add to Zone)

This is the only Talk group you will need for a QSO on the reflector.

### **To link and unlink the reflector.**

Do a Manual Dial -

Go to Menu - Contact - Manual Dial - enter reflector number **4xxx** - transmit for 1 second.  
The repeater should respond with a voice announcement, "Connect to reflector 4xxx".  
Then go back to Talk Group 9 to make a QSO.

or

Program the radio with the [Reflector number](#) as a PRIVATE call in contacts.

To link to a reflector.

Select the reflector number from the contacts list and transmit for about 1 second.  
The repeater should respond with a voice announcement, "Connect to reflector 4xxx".  
Then go back to Talk Group 9 to make a QSO.

To unlink select 4000 from the contacts list, transmit for about 1 second, and you should hear a voice announcement "Reflector Disconnected".

To enquire about the reflector link status call 5000, and the repeater will respond with the currently linked reflector.

## **Time Slot 2 (Reflectors on Brandmeister)**

TG 9 - UK Wide Call on [4400 by default](#).\*

After contact please move to a Reflectors below.

User Activated Reflectors on Slot 2.

4401 - Chat 1

4402 - Chat 2

4403 - Chat 3

4404 - Ireland

4405 - Scotland

4407 - Wales

4410 - S.West

4411 - S.East

4412 - North West

4414 - Ireland Chat

4415 - Scotland Chat

4416 - North East

4417 - Wales Chat

4418 - W.Midlands

4419 - E.Midlands

4420 - Wires X Room 27753

4426 - Allstar Link

4429 - TEST

4000 - Disconnect (Should be GROUP CALL in your contacts)

\* Some Repeaters offer other [defaults](#)

[Link to all Brandmeister Reflectors](#)

**Do not use any other Talk Groups on Slot 2**