

Link to Reflectors

Time Slot 2 implements the use of reflectors similar to the D-star network.

The way to use the reflector is to program your radio with Talk Group 9 in Time Slot 2.
(Add 9 in contact as GROUP. Make a Channel up for TG9. Add to Zone)

This is the only Talk group you will need for a QSO on the reflector.

To link and unlink the reflector.

Do a Manual Dial -

Go to Menu - Contact - Manual Dial - enter reflector number 4xxx - transmit for 1 second.
The repeater should respond with a voice announcement, "Connect to reflector 4xxx".
Then go back to Talk Group 9 to make a QSO.

or

Program the radio with the Reflector number as a PRIVATE call in contacts.

To link to a reflector.

Select the reflector number from the contacts list and transmit for about 1 second.
The repeater should respond with a voice announcement, "Connect to reflector 4xxx".
Then go back to Talk Group 9 to make a QSO.

To unlink select 4000 from the contacts list, transmit for about 1 second, and you should hear a voice announcement "Reflector Disconnected".

To enquire about the reflector link status call 5000, and the repeater will respond with the currently linked reflector.