

Access Talk Groups

You have a few options via an Anytone Radio to Call up a Talk Group.

Option 1

Add as a Channel to the radio

http://hamradio.joomla.com/images/Anytone/Add_Talk_Groups.pdf

Option 2

Press and hold 0 key (New window opens. Private ID)

Press # key = Talk Group ID

Type in Talk Group Number (2350 UK, 91 World Wide etc)

PTT and now you're on 2350

CPS – Optional Setting – Digital Fun

868 – Set *Group Call Hold Time* to 30mins

878 and 578 – Set *Dial Group Hold* to 30mins

Option 3

Click on List key (RED)

Scroll down or up till you find the Talk Group you wish to use.

Press PTT and now you're on that Talk Group

You need to have the Talk Group added to the CPS - Talk Groups (*See Option 1*)

CPS – Optional Setting – Digital Fun

868 – Set *Group Call Hold Time* to 30mins

878 and 578 – Set *Group Call Hold Time* to 30mins

Option 4

Is the same as Option 3 but going via the Menu Key.

Menu Key (Green) - Talk Groups - TG List

Option 5

Last Call Reply

CPS – Optional Setting – Key Function -

Set a Key to – LastCall Reply

CPS – Optional Setting – Digital Fun

868 – Set *Group Call Hold Time* to 30mins

878 and 578 – Set *Dial Group Hold* to 30mins

With Digi Moni turned on for Single or Double Slot.
When a call comes in on another Talk Group/Private Call you press the Function Key and the radio is now locked to that Talk Group/Private Call.
Just PTT and your on that Talk Group or Private Call.

Info

[List of Brandmeister Talk Groups](#)

[List of Phoenix UK Talk Groups.](#)

<http://tiny.cc/AnytoneDMR>