

Sending Talker Alias

Go to SelfCare and log in

<https://brandmeister.network/?page=selfcare>

All we need to do is change the APRS Text

Most common is

Your name (Adam)

(BM sends your Callsign now)

You can enter up to 20 characters/spaces and that includes your call.

M6xxx Adam xxxxxxxxUSA = (20)

The screenshot shows the BrandMeister SelfCare interface. On the left is a dark sidebar with navigation options: User Dashboard, Last Heard, Repeaters, Hotspots, Masters, Alerts, Data Visualisation, Information, Services, Hose line, Extended Routing, Extended Routing (Old version), SelfCare, Hotspot, and My hotspots. The main content area is titled 'SelfCare' and shows settings for two different IDs. Each section is titled 'SelfCare settings for ID'. The top section is for ID 2342665, and the bottom section is for ID 2352805. Both sections have the same layout: 'Brand' (Hytera), 'Language' (English), 'APRS Interval' (270 sec for the top, 60 sec for the bottom), and 'APRS Callsign' (empty). The 'APRS Icon' is set to a microphone icon. A red arrow points from the microphone icon to the 'APRS Text' field, which contains 'Adam xxxxxxxx'. Below each section are two buttons: 'Save changes for ID [ID number]' and 'Restore defaults'.

Does not work (yet)

Motorola Repeaters (possible, but it has issues with decoding audio streams)

Does not work (no possibilities)

c-Bridge CC-CC Link (protocol limitation)

RadioActivity KAIROS (protocol limitation)

DV4*

[Full info and updates on this link](#)