

Reflectors same as D-Star

Slot 2 via TG9 is just the same as D-Star

Add – TG9 as a group call in your contact list = *D-Star CQCQCQ*

- a. [Examples of D-Star radio setting on this link](#)
- b. [BM reflectors](#)
- c. [Phoenix reflectors](#)

You move BM Reflectors the same way you would with D-Star

If you want Ref 4401 = *D-star lets call it REF001C*

As shown in (b. Moving BM reflectors) above

After you have keyed up for 1 second, you get the voice confirmation, go back to TG9 To talk = *D-star CQCQCQ*

Depending on the hang time in the radio it will by default return to TG9,

BUT I always just turn the channel knob one right and back again to speed things up.

Now you can talk on TG9 to Reflector 4401.

DTMF tones, IS NOT used in DMR Radios or Brandmeister.

DMR uses – Menu – Contacts – Manual Dial – Type in 4401 and press the PTT

DO NOT hit confirm or any other key, **Just the PTT** for 1 second.

To talk on other Reflectors just follow the steps above again (4402, 4403, 4639 etc)

Commands:

Ref 4000 Disconnect = *D-Star U* (Do this before moving to new Reflectors)

Ref 5000 Status = *D-Star I*

Ref 9990 Echo = *D-Star E*